


# PowerVerter Ultra-Compact Inverter

Portable Power for All Applications



## Model #: PV1000HF

- ▶ 12V DC input; 120V AC output; 4 outlets
- ▶ 1000 watts continuous output
- ▶ 2000 watts peak output
- ▶ Powers an entire mobile office or kitchen

## DESCRIPTION

Harness your vehicle's battery to efficiently power office equipment on the road or power tools at a work site. Continuously supplies up to 1000 watts of 120V AC power to 4 AC outlets from any 12V battery. Includes a set of DC terminals for simple installation. Compact, lightweight metal case design is among the smallest, most rugged inverters available at this power level.

## KEY BUYING POINTS

- Allows users to run AC appliances from any properly-sized 12V battery or automotive DC system
- Converts 12V DC battery power to 120V AC power
- 1000 watts continuous output power; 2000 watts peak output power
- 4 outlets
- Compact, lightweight design with all-metal housing
- Remote control jack provides optional remote monitoring and control when used with optional remote module (APSRM4, sold separately)
- Low battery alarm with auto-shutoff prevents deep battery discharge
- High-efficiency operation conserves batteries to prolong run time
- Battery charge level LEDs indicate the approximate charge level (high/medium/low) of connected batteries
- Connected load level LEDs indicate the approximate wattage load level (high/medium/low) of connected equipment
- Operating mode switch controls inverter operation
- Battery Charge Conservation Dial conserves battery power by setting the load-level at which the inverter automatically shuts off
- Cooling fan regulates internal temperature and prolongs service life
- Mounting flanges provide safe, fixed installation
- Grounding lug connects to vehicle ground
- Grooved cooling surface provides additional surface area for more efficient cooling

## TYPICAL APPLICATIONS

- Ideal for TVs, DVD players, small microwaves, power tools, small coffeemakers, game systems, desktop computers, laptops, portable electronics, lighting and other AC applications under 1000 watts.

## OPTIONS & ACCESSORIES

- APSRM4 Remote Control Module (sold separately)

## PACKAGE INCLUDES

- PV1000HF Inverter
- Warranty information
- Instruction manual

## COMPLETE SPECIFICATIONS

### SYSTEM OVERVIEW

<b>System overview:</b>	Compact 12 volt DC to 120 volt AC power inverter. 1000 watts continuous / 2000 watts peak. Requires hardwire DC installation, 4 AC outlets
<b>Voltage compatibility:</b>	Compatible with 12VDC automotive or battery power sources
<b>Frequency compatibility:</b>	60 Hz

### OUTPUT

<b>Output watt capacity (watts):</b>	1000 watts continuous, supports instantaneous peak output up to 2000 watts
<b>Output nominal voltage:</b>	120V nominal
<b>Output voltage regulation:</b>	Maintains PWM sine wave output voltage of 115 VAC (+/- 8 VAC)
<b>Output frequency regulation:</b>	60 Hz (+/-3 Hz)
<b>Outlet quantity / type:</b>	Includes 4 NEMA 5-15R output receptacles
<b>Overload protection:</b>	Automatic overload protection shuts down inverter system in the event of overloads. Inverter and electrical system are further protected via four internal 40A automotive fuses

### INPUT

<b>Maximum input amps / watts:</b>	Full continuous load - 100A at 12V DC, No load - 1.5A at 12V DC, Shutdown / load sense mode - 100 microamps
<b>Input connection type:</b>	Set of 2 DC bolt-down wiring terminals
<b>Input cord length:</b>	User supplies cabling. Minimum gauges for full load operation: 4 (12 ft max), 2 (20 ft max), 0 (31 ft max).
<b>Recommended electrical service:</b>	Requires 12V DC input source capable of delivering 100A for the required duration (when used at full capacity). For automotive applications, professional hardwire installation with 175A battery system fusing is recommended.

### BATTERY

<b>DC system voltage:</b>	DC input operating range 10-15VDC. Alarm sounds as voltage drops to 10.5V. Auto-shutdown occurs at 10V.
---------------------------	---

### LEDS ALARMS & SWITCHES

<b>Front panel LEDs:</b>	Set of 6 LEDs offer continuous status information on battery and connected load conditions
<b>Alarms:</b>	Dual function alarm indicates overload conditions or low DC input voltage of 10.5V or less
<b>Switches:</b>	3 position rocker switch enables on/off power control, plus "remote" setting which enables inverter to be remotely powered on or off when used in conjunction with APSRM4 Remote Control Module (sold separately)

### PHYSICAL

<b>Shipping weight (lbs):</b>	5.6
<b>Shipping weight (kg):</b>	2.5
<b>Unit weight (lbs):</b>	5
<b>Unit weight (kg):</b>	2.1
<b>Unit Dimensions (HWD/in):</b>	3.75 x 6 x 12.5
<b>Unit Dimensions (HWD/cm):</b>	9.5 x 15.2 x 31.8
<b>Shipping Dimensions (HWD/in):</b>	4 x 6.5 x 13
<b>Shipping Dimensions (HWD/cm):</b>	10.2 x 16.5 x 33
<b>Material of construction:</b>	Aluminum / sheet metal
<b>Form factors supported:</b>	Mounting slots enable permanent placement of inverter on any horizontal surface (see manual for additional mounting information)

**Cooling method:** Fan

## **ENVIRONMENTAL**

**Operating Temperature:** 32-104 Fahrenheit / 0-40 Celcius

**Relative Humidity:** 0-95% non-condensing

## **WARRANTY**

**Product warranty:** 1 year (Outside the U.S. and Canada, call for warranty information)

## **SPECIAL FEATURES**

**TVSS grounding:** Grounding lug grounds the inverter to vehicle or earth ground - user supplies cabling

**Appearance:** Attractive, rugged, metallic gray color inverter system

**Load Sensing:** Optional load sense function conserves battery power by setting the load-level at which the inverter automatically shuts off

*The policy of Tripp Lite is one of continuous improvement.  
Specifications are subject to change without notice.  
Therefore, your product may vary slightly from what is currently listed.*



**Tripp Lite World Headquarters**  
1111 W. 35th Street  
Chicago, IL 60609 USA

**Customer Support**  
(773) 869-1234

© 2007 Tripp Lite. All Rights Reserved.